

## Annotation Note

### Update to kernel 2.6.26

1. copy zImage to /boot/zImage
2. remove hotplug daemon “apt-get remove --purge hotplug”
3. install udev “apt-get install udev”
4. open /etc/udev/rules.d/z45\_persistent-net-generator.rules
5. comment out following lines:  
#KERNEL=="eth\*|ath\*|wlan\*|ra\*|sta\*", DRIVERS=="?\*",\  
# IMPORT {program}="write\_net\_rules \$attr{address}"
6. delete all entries in /etc/udev/rules.d/z25\_persistent-net.rules
7. create /etc/udev/rules.d/custom.rules with following content:  
KERNEL=="rtc0", SYMLINK+="rtc"  
KERNEL=="i2c-0", SYMLINK+="i2c"
8. reboot